



- There will be 20s alert when alarm time is over.
- If there is no key operation for 60 second, Setting Mode will be exit and returned to Alarm Display Mode.

## 5. Dual time

- Press C key for 2 seconds to enter into the Dual time setting mode," Hour " flashing when loading , Press C key to select item as following sequence :  
Minute → 12H/24H
- Press B key to adjust the flashing.
- If there is no key operation for 60 second, Setting Mode will be exit and returned to Dual Time Display Mode.

## 6. Chronograph

- Press C key to Start/Stop running ;
- When stop , press C key for 2 seconds zero .

## C. Specifications

- Module Size :  $\Phi 33.2\text{mm}$
- Module Thickness :  $7.95\pm 0.15\text{mm}$
- Operational Temperature Range :  $-10^{\circ}\text{C} \sim 60^{\circ}\text{C}$
- Operational Voltage : 3.0V
- Accuracy :  $\pm 90\text{sec/month}$
- Battery Code : CR2025
- Current Consumption for Digit (maxima) :  $\leq 3.5 \mu\text{A}(T=25^{\circ}\text{C})$
- Current Consumption for Digit (averagely) :  $\leq 2.5 \mu\text{A}(T=25^{\circ}\text{C})$
- Alarm Current :  $\leq 2.5 \text{mA}$
- EL Current :  $\leq 10 \text{mA}$
- Battery life : 3 backlight operation (6 seconds) per day : 24 month (Japan Lithium)  
20 seconds of alarm operation per day

	Prepared	Checked	Approve
Name	冯碧颜	徐治中	宋检望
Date	08/11/29	08/11/29	08/11/29