

MODE (A Key)

——



——

(B Key) SET

A . Features


- 5.5 Digits LCD Display, Display Hour ,Minute ,Second ,Month and Day .

B . Operational Manual

1. In Real Time Mode,press A key once displaying Date

2. Time Setting

- In Real Time Mode ,Press B key once to entry Time Setting mode ,select item in turn as following :



- Press A key to adjust the flashing item.
- As setting seconds,the flashing seconds can be reset to zero by pressing A key and will return back to Real Time Mode automatically.
- Press A key while the seconds are in the range of 30 to 59 resets them to 00 and adds 1 to the minutes . In the range of 00 to 29,the minutes are unchanged.

C. Specifications

- Module Size : 24*14.1mm
- Module Thickness : 4.60mm
- Operational Temperature Range : -10℃~60℃
- Operational Voltage : 1.5V
- Accuracy : ±60sec/month
- Battery Code : V371(capacitance: 35m Ah)
- static average current : ≤0.87u A (static maximum current : 2.5uA)
- Battery life : ≥24 month

	Prepared	Checked	Approve
Name	冯碧颜	徐治中	宋检望
Date	11/07/28	11/08/11	11/08/11