

LIGHT/ADJ (A Key)



(B Key) MODE

A . Features

- 5.5 Digits LCD Display, Display Hour ,Minute ,Second ,Month and Day .

B . Operational Manual

1. At any state ,press A key EL backlight for 3s .

2. In Real Time Mode,press A key once displaying Date

3. Time Setting

- In Real Time Mode ,Press B key once to entry Time Setting mode ,select item in turn as following :
Second → Hour → Minute → Month → Day
- Press A key to adjust the flashing item
- As setting seconds,the flashing seconds can be reset to zero by pressing A key and will return back to Real Time Mode automatically.
- Press A key while the seconds are in the range of 30 to 59 resets them to 00 and adds 1 to the minutes . In the range of 00 to 29,the minutes are unchanged.

C. Specifications

- Module Size : 33.6*17.6mm
- Module Thickness (include buzzer) : 6.80mm
- Operational Temperature Range : -10°C~60°C
- Operational Voltage : 1.5V
- Accuracy : ±30sec/month
- Battery Code : V391MF(capacitance: 42m Ah)
- static average current : ≤1.00u A (static maximum current : 2.5uA)
- EL lighten average current : ≤5.09m A (ELlighten maximum current : 10.0mA)
- Battery life (90%) : ≥18 month

(Battery life calculate according to EL lighten four time each day for 3 second each time)

	Prepared	Checked	Approve
Name	冯碧颜	徐治中	宋检望
Date	08/06/27	08/06/27	08/06/27