

LIGHT (C Key) ———



———— (B Key) MODE

———— (A Key) SET

A . Features

- 5.5 Digits LCD Display, Display Hour ,Minute ,Second ,Month and Day .

B . Operational Manual

1. At any state ,press C key EL backlight for 3s .

2. In Real Time Mode,press B key once displaying Date

3. Time Setting

- In Real Time Mode ,Press A key once to entry Time Setting mode ,select item in turn as following :
Second → Hour → Minute → Month → Day
- Press B key to adjust the flashing item
- As setting seconds,the flashing seconds can be reset to zero by pressing B key and will return back to Real Time Mode automatically.
- Press B key while the seconds are in the range of 30 to 59 resets them to 00 and adds 1 to the minutes . In the range of 00 to 29,the minutes are unchanged.

C. Specifications

- Module Size : 32.2×32.2 mm
- Module Thickness : 2.9±0.05mm
- Operational Temperature Range : -10℃~60℃
- Operational Voltage : 1.5V
- Accuracy : ±60sec/month
- Battery Code : V371
- Current Consumption for Digit (maxima) : ≤2.3 u A(T=25℃)
- Current Consumption for Digit (averagely) : ≤1.5 u A(T=25℃)
- EL Current : ≤10 mA
- Battery life (3 backlight operation (6 seconds) per day) : 18 month

	Prepared	Checked	Approve
Name	冯碧颜	徐治中	宋检望
Date	08/01/07	08/01/07	08/01/07