



—— (B Key) MODE

—— (A Key) SET

A . Features

- 3.5 Digits LCD Display, Display Hour ,Minute ,Second ,Month and Day .

B . Operational Manual

1. At time setting mode ,press B key to activate auto advance function.
2. press B key once displaying Date ;twice displaying Second , Press B key again to return to Real Time mode .

3. TIME SETTING

- Press A key twice to entry Time Setting mode ,select item in turn as following :
 Month → Day → Hour → Minute
- Press B key to adjust the flashing item.
- Press A key to confirm.

C. Specification

- Dimension : 21.10*28.10mm
- Thickness (exclude buzzer) : 3.80mm
- Working temperature : -10℃~+60℃
- Working voltage : 1.5V
- Time accuracy : ±90S/Month
- Battery type : 373 RENATA(Capacity:29mAh)
- Average Static current : ≤2.09u A (Maximum static current: 2.8 u A)
- Battery Life (90%) : ≥18 Months

	Prepared	Checked	Approved
Name	冯碧颜	徐治中	宋检望
Date	12/06/29	12/06/29	12/06/29