

# **BJ2924** MOVEMENT INSTRUCTION





(C Key) MODE

(B Key) DATE

(A Key) SET

## A . Features

- 3 Mode: Time Keeping, Month-Date, LED full display.
- Time Keeping function counts and displays: minutes and hours.
- 12-hour format.
- 3 keys operation, Low power dissipation.

## **B** . General Guide

- press "A" to view LED full display.
- press "C" to view the current hour and minute.
- press "B" to view the current month and date.

### **Tinekeeping**

Use the Time keeping Mode to set and view the current hours and minutes .

#### To set the time

- In the timekeepign mode .Hold down A key until the hours and minutes start to flash together, which indicates the setting screen.
- Press C to increase the hour setting; Press B to increase the minute setting.
- With the 12-hour format ,the PM indicator appears to the left of the hour digits for times in the rnge of noon to 11: 59 p.m.
- With the 12-hour format, the AM indicator appears to the left of the hour digits for times in the range of noon to 11: 59 a.m.

## **Month-Date**

Use the Time Month-Date Mode to set and view the current months and dates.

#### To set the date

- In the Time Month-Date Mode .Hold down A key until the month and date start to flash together ,which indicates the setting screen.
- Press C to increase the Month setting; Press B to increase the Date setting.

## C. Specifications

➤ Module Size

Module Thickness

Operational Temperature Range

Operational Voltage

Accuracy

**Battery Code** 

Current Consumption for Digit

Alarm Current

LED Current

Battery life 12 backlight operation (3 seconds) per day

: 30.9\*23.9mm

:  $5.95 \pm 0.15 \,\mathrm{mm}$ 

: -10°C ~+60°C

: 3.0V

 $\pm 90 \text{ sec/month}$ 

: CR2025

:  $\leq 2.0$  u A (T=25°C)

: ≤20.0 mA

: 18 month (Japan Lithium)

	Prepared	Checked	Approve
Name	冯碧颜	韦章龙	刘成恒
Date	06/09/04	06/09/04	06/09/04

2006-09-04 Model: BJ2924 Page: 1 / 2 Edition: A